

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 40 22B SERIES-100 TO 240VAC

IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	100-120V AC, 1-Phase Input - 0-230V, 3-Phase Output					
		Output Ratings		Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps		kVA	Amps	
22B-V2P3N104	22B-V2P3F104	0.4 (0.5)	2.3	90-132	1.15	9	HSJ15
22B-V5P0N104	22B-V5P0F104	0.75 (1.0)	5	90-132	2.45	20.3	HSJ35
22B-V6P0N104	22B-V6P0F104	1.1 (1.5)	6	90-132	3	24	HSJ40

IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	200-240V AC, 1-Phase Input - 0-230V, 3-Phase Output					
		Output Ratings		Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps		kVA	Amps	
22B-A2P3N104	-	0.4 (0.5)	2.3	180-264	1.15	6	HSJ10
22B-A5P0N104	-	0.75 (1.0)	5	180-264	2.45	12	HSJ20
22B-A8P0N104	-	1.5 (2.0)	8	180-264	4	18	HSJ30
22B-A012N104	-	2.2 (3.0)	12	180-264	5.5	25	HSJ40

IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	200-240V AC, 3-Phase Input - 0-230V, 3-Phase Output					
		Output Ratings		Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps		kVA	Amps	
22B-B2P3N104	22B-B2P3F104	0.4 (0.5)	2.3	180-264	1.15	2.5	HSJ6
22B-B5P0N104	22B-B5P0F104	0.75 (1.0)	5	180-264	2.45	5.7	HSJ10
22B-B8P0N104	22B-B8P0F104	1.5 (2.0)	8	180-264	4	9.5	HSJ15
22B-B012N104	22B-B012F104	2.2 (3.0)	12	180-264	5.5	15.5	HSJ25
22B-B017N104	22B-B017F104	3.7 (5.0)	17.5	180-264	8.6	21	HSJ30
22B-B024N104	22B-B024F104	5.5 (7.5)	24	180-264	11.8	26.1	HSJ40
22B-B033N104	22B-B033F104	7.5 (10.0)	33	180-264	16.3	34.6	HSJ60

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 40 22B SERIES-380 TO 600VAC

380-480V AC, 3-Phase Input - 0-460V, 3-Phase Output							
IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	Output Ratings		Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps		kVA	Amps	
22B-D1P4N104	22B-D1P4F104	0.4 (0.5)	1.4	342-528	1.4	1.8	HSJ3
22B-D2P3N104	22B-D2P3F104	0.75 (1.0)	2.3	342-528	2.3	3.2	HSJ6
22B-D4P0N104	22B-D4P0F104	1.5 (2.0)	4	342-528	4	5.7	HSJ10
22B-D6P0N104	22B-D6P0F104	2.2 (3.0)	6	342-528	5.9	7.5	HSJ15
22B-D010N104	22B-D010F104	4 (5.0)	10.5	342-528	10.3	13	HSJ20
22B-D012N104	22B-D012F104	5.5 (7.5)	12	342-528	11.8	14.2	HSJ25
22B-D017N104	22B-D017F104	7.5 (10.0)	17	342-528	16.8	18.4	HSJ30
22B-D024N104	22B-D024F104	11 (15.0)	24	342-528	23.4	26	HSJ50

460-600V AC, 3-Phase Input - 0-575V, 3-Phase Output							
IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	Output Ratings		Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps		kVA	Amps	
22B-E1P7N104	22B-E1P7F104	.75 (1.0)	1.7	414-660	2.1	2.3	HSJ6
22B-E3P0N104	22B-E3P0F104	1.5 (2.0)	3	414-660	3.65	3.8	HSJ6
22B-E4P2N104	22B-E4P2F104	2.2 (3.0)	4.2	414-660	5.2	5.3	HSJ10
22B-E6P6N104	22B-E6P6F104	4 (5.0)	6.6	414-660	8.1	8.3	HSJ15
22B-E9P9N104	22B-E9P9F104	5.5 (7.5)	9.9	414-660	12.1	11.2	HSJ20
22B-E012N104	22B-E012F104	7.5 (10.0)	12.2	414-660	14.9	13.7	HSJ25
22B-E019N104	22B-E019F104	11 (15.0)	19	414-660	23.1	24.1	HSJ40

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 70 20AB-20AC SERIES

208VAC-240VAC-400VAC

Part # 208VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Fuses
20AB2P2	0.5	0.33	2.9	HSJ6
20AB4P2	1	0.75	5.6	HSJ10
20AB6P8	2	1.5	10	HSJ15
20AB9P6	3	2	14	HSJ20
20AB015	5	3	16	HSJ20
20AB022	7.5	5	23.3	HSJ30
20AB028	10	7.5	29.8	HSJ40

Part # 240VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Fuses
20AB2P2	0.5	0.33	2.9	HSJ6
20AB4P2	1	0.75	5.6	HSJ10
20AB6P8	2	1.5	10	HSJ15
20AB9P6	3	2	14	HSJ20
20AB015	5	3	16	HSJ20
20AB022	7.5	5	23.3	HSJ30
20AB028	10	7.5	29.8	HSJ40

Part # 400VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Fuses
20AC1P3	0.37	0.25	1.6	HSJ3
20AC2P1	0.75	0.55	2.5	HSJ6
20AC3P5	1.5	1.1	4.3	HSJ10
20AC5P0	2.2	1.5	6.5	HSJ15
20AC8P7	4	3	11.3	HSJ15
20AC011	5.5	4	11	HSJ15
20AC015	7.5	5.5	15.1	HSJ20
20AC022	11	7.5	21.9	HSJ30
20AC030	15	11	30.3	HSJ40
20AC037	18.5	15	35	HSJ50
20AC043	22	18.5	40.7	HSJ60

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 70 20AD-20AE SERIES

480 TO 600VAC

Part # 480VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Fuses
20AD1P1	0.5	0.33	1.3	HSJ3
20AD2P1	1	0.75	2.4	HSJ6
20AD3P4	2	1.5	3.8	HSJ6
20AD5P0	3	2	5.6	HSJ10
20AD8P0	5	3	9.8	HSJ15
20AD011	7.5	5	9.5	HSJ15
20AD015	10	7.5	12.5	HSJ20
20AD022	15	10	19.9	HSJ25
20AD027	20	15	24.8	HSJ35
20AD034	25	20	34	HSJ40
20AD040	30	25	40	HSJ50

Part # 600VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Fuses
20AE0P9	0.5	0.33	1.3	HSJ3
20AE1P7	1	0.75	1.9	HSJ6
20AE2P7	2	1.5	3	HSJ6
20AE3P9	3	2	4.4	HSJ10
20AE6P1	5	3	7.5	HSJ15
20AE9P0	7.5	5	7.7	HSJ15
20AE011	10	7.5	9.8	HSJ15
20AE017	15	10	15.3	HSJ20
20AE022	20	15	20	HSJ25

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 400 22C SERIES- 200 TO 480VAC

100-120V AC, 1-Phase Input - 0-230V, 3-Phase Output								
IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	Output Ratings			Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps 45°C	50°C		kVA	Amps	
22C-B012N103	22C-B012F103	2.2 (-3)	12	12	180-265	6.5	15.5	HSJ20
22C-B017N103	22C-B017F103	3.7 (5.0)	17.5	17.5	180-265	8.8	21	HSJ30
22C-B024N103	22C-B024F103	5.5 (7.5)	24	24	180-265	10.9	26.1	HSJ35
22C-B033N103	22C-B033F103	7.5 (10)	33	33	180-265	14.4	34.6	HSJ45
22C-B049A103	-	11 (15)	49	49	180-265	21.3	51	HSJ70
22C-B065A103	-	15 (20)	65	65	180-265	28.3	68	HSJ90
22C-B075A103	-	18.5 (25)	75	75	180-265	32.5	78	HSJ100
22C-B090A103	-	22 (30)	90	81	180-265	38.3	92	HSJ125
22C-B120A103	-	30 (40)	120	120	180-265	51.6	124	HSJ175
22C-B145A103	-	37 (50)	145	130	180-265	62.4	150	HSJ200

380-480V AC, 3-Phase Input - 0-460V, 3-Phase Output								
IP/20 NEMA Type Open Catalog Number	Flange Mount Catalog Number	Output Ratings			Voltage Range	Input Ratings		Main Fuse
		kW (HP)	Amps 45°C	50°C		kVA	Amps	
22C-D6P0N103	22C-D6P0F103	2.2 (3.0)	6	6	340-528	6.3	7.5	HSJ10
22C-D010N103	22C-D010F103	4 (5.0)	10.5	10.5	340-528	10.9	13	HSJ20
22C-D012N103	22C-D012F103	5.5 (7.5)	12	12	340-528	11.9	14.2	HSJ20
22C-D017N103	22C-D017F103	7.5 (10)	17	17	340-528	15.3	18.4	HSJ25
22C-D022N103	22C-D022F103	11 (15)	22	22	340-528	19.2	23	HSJ30
22C-D030N103	22C-D030F103	15 (20)	30	27	340-528	25.8	31	HSJ40
22C-D038A103	-	18.5 (25)	38	38	340-528	33.3	40	HSJ50
22C-D045A103	-	22 (30)	45.5	45.5	340-528	39.1	47	HSJ60
22C-D060A103	-	30 (40)	60	54	340-528	53.3	64	HSJ80
22C-D072A103	-	37 (50)	72	72	340-528	60.7	73	HSJ100
22C-D088A103	-	45 (60)	88	88	340-528	74.9	90	HSJ125
22C-D105A103	-	55 (75)	105	105	340-528	89	107	HSJ150
22C-D142A103	-	75 (100)	142	128	340-528	124.8	150	HSJ200
22C-D170A103	-	90 (125)	170	170	340-528	142	170	HSJ250
22C-D208A103	-	110 (150)	208	208	340-528	167	200	HSJ250

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 700 20BB SERIES

208 TO 240VAC

Part # 208VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20BB2P2	0.5	0.33	1.9	HSJ3
20BB4P2	1	0.75	3.7	HSJ6
20BB6P8	2	1.5	6.8	HSJ15
20BB9P6	3	2	9.5	HSJ15
20BB015	5	3	15.7	HSJ20
20BB022	7.5	5	23	HSJ30
20BB028	10	7.5	29.6	HSJ40
20BB042	15	10	44.5	HSJ60
20BB052	20	15	51.5	HSJ80
20BB070	25	20	72	HSJ90
20BB080	30	25	84.7	HSJ110
20BB104	40	–	113	HSJ150
20BB104*	–	30	84.7	HSJ125
20BB130	50	–	122	HSJ175
20BB130*	–	40	98	HSJ125
20BB154	60	–	167	HSJ225
20BB154*	–	50	141	HSJ200
20BB192*	75	–	208	HSJ300
20BB192*	–	60	167	HSJ225

Part # 240VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20BB2P2	0.5	0.33	1.7	HSJ3
20BB4P2	1	0.75	3.3	HSJ6
20BB6P8	2	1.5	5.9	HSJ10
20BB9P6	3	2	8.3	HSJ15
20BB015	5	3	13.7	HSJ20
20BB022	7.5	5	19.9	HSJ30
20BB028	10	7.5	25.7	HSJ35
20BB042	15	10	38.5	HSJ50
20BB052	20	15	47.7	HSJ60
20BB070	25	20	64.2	HSJ90
20BB080	30	25	73.2	HSJ100
20BB104	40	–	98	HSJ125
20BB104*	–	30	73	HSJ100
20BB130	50	–	122	HSJ175
20BB130*	–	40	98	HSJ125
20BB154	60	–	145	HSJ200
20BB154*	–	50	122	HSJ175
20BB192	75	–	180	HSJ225
20BB192*	–	60	145	HSJ200
ACS550-U2-526A-4	450	400	477	A6T700
ACS550-U2-602A-4	500	450	515	A6T700
ACS550-U2-645A-4	550	500	590	A6T800

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 700 20BC SERIES

400VAC

Part # 208VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20BC1P3	0.37	0.25	1.1	HSJ3
20BC2P1	0.75	0.55	1.8	HSJ6
20BC3P5	1.5	0.75	3.2	HSJ6
20BC5P0	2.2	1.5	4.6	HSJ10
20BC8P7	4	2.2	7.9	HSJ15
20BC011	5.5	4	10.8	HSJ15
20BC015	7.5	5.5	14.4	HSJ20
20BC022	11	7.5	20.6	HSJ30
20BC030	15	11	28.4	HSJ35
20BC037	18.5	15	35	HSJ45
20BC043	22	18.5	40.7	HSJ60
20BC056	30	22	53	HSJ70
20BC072	37	30	68.9	HSJ90
20BC085	45	–	81.4	HSJ110
20BC085*	–	37	68.9	HSJ90
20BC105	55	–	100.5	HSJ125
20BC105*	–	45	81.4	HSJ110
20BC125	55	–	121.1	HSJ150
20BC125*	–	45	91.9	HSJ125
20BC140	75	–	149	HSJ200
20BC140*	–	55	111	HSJ150
20BC170	90	–	164	HSJ250
20BC170*	–	75	136	HSJ200
20BC205	110	–	199	HSJ250
20BC205*	–	90	164	HSJ250
20BC260	132	–	255	HSJ350
20BC260*	–	110	199	HSJ250

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 700 20BD SERIES

480VAC

Part # 480VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20BD1P1	0.5	0.33	0.9	HSJ3
20BD2P1	1	0.75	1.6	HSJ3
20BD3P4	2	1.5	2.6	HSJ6
20BD5P0	3	2	3.9	HSJ6
20BD8P0	5	3	6.9	HSJ15
20BD011	7.5	5	9.5	HSJ15
20BD014	10	7.5	12.5	HSJ17-1/2
20BD022	15	10	19.9	HSJ25
20BD027	20	15	24.8	HSJ35
20BD034	25	20	31.2	HSJ40
20BD040	30	25	36.7	HSJ50
20BD052	40	30	47.7	HSJ60
20BD065	50	40	59.6	HSJ80
20BD077*	–	50	59.6	HSJ80
20BD077	60	–	72.3	HSJ100
20BD096*	–	60	72.3	HSJ100
20BD096	75	–	90.1	HSJ125
20BD125*	–	75	90.1	HSJ125
20BD125	100	–	117	HSJ150
20BD156*	–	100	131	HSJ175
20BD156	125	–	147	HSJ200
20BD180*	–	125	147	HSJ200
20BD180	150	–	169	HSJ225
20BD248	200	–	233	HSJ300
20BD248*	–	150	169	HSJ225

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 700 20BE SERIES

600VAC

Part # 600VAC	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20BE0P9	0.5	0.3	0.7	HSJ1
20BE1P7	1	0.5	1.3	HSJ3
20BE2P7	2	1	2.1	HSJ3
20BE3P9	3	2	3	HSJ6
20BE6P1	5	3	5.3	HSJ10
20BE9P0	7.5	5	7.8	HSJ15
20BE011	10	7.5	9.9	HSJ15
20BE017	15	10	15.4	HSJ20
20BE022	20	15	20.2	HSJ30
20BE027	25	20	24.8	HSJ35
20BE032	30	25	29.4	HSJ40
20BE041	40	30	37.6	HSJ50
20BE052	50	40	47.7	HSJ60
20BE062	60	50	58.2	HSJ80
20BE077	75	–	72.3	HSJ90
20BE077*	–	60	58.2	HSJ90
20BE099	100	–	92.9	HSJ125
20BE099*	–	75	72.3	HSJ100
20BE125	125	–	117	HSJ150
20BE125*	–	100	92.9	HSJ125
20BE144	150	–	135	HSJ175
20BE144*	–	125	117	HSJ150

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 700 DC COMMON BUS

540VDC-650VDC

540 Volt DC Input	kW Normal Duty	kW Heavy Duty	I _(A) DC Input	I _(A) DC Output	I _(A) 1 Minute	I _(A) 3 Seconds	Fuses
20BC8P7	4	3	9.3	8.7	9.9	13.2	HSJ20
20BC011	5.5	4	12.6	11.5	13	17.4	HSJ25
20BC015	7.5	5.5	16.8	15.4	17.2	23.1	HSJ30
20BC022	11	7.5	24	22	24.2	33	HSJ45
20BC030	15	11	33.2	30	33	45	HSJ60
20BC037	18.5	15	40.9	37	45	60	HSJ80
20BC043	22	18.5	47.5	43	56	74	HSJ90
20BC056	30	22	61.9	56	64	86	HSJ110
20BC072	37	30	80.5	72	84	112	HSJ150
20BC085	–	37	80.5	72	108	144	HSJ150
20BC085	45	–	95.1	85	94	128	HSJ200
20BH105	–	45	95.1	85	128	170	HSJ200
20BH105	55	–	117.4	105	116	158	HSJ200
20BH125	–	45	91.9	96	144	168	HSJ150
20BH125	55	–	139.8	125	138	163	HSJ225
20BH140	–	55	117.4	105	158	210	HSJ200
20BH140	75	–	158.4	140	154	210	HSJ300
20DH170	–	75	158.4	140	210	280	HSJ300
20DH170	90	–	192.4	170	187	255	HSJ350
20DH205	–	90	192.4	170	255	313	HSJ350
20DH205	110	–	232	205	220	289	HSJ400

650 Volt DC Input	kW Normal Duty	kW Heavy Duty	I _(A) DC Input	I _(A) DC Output	I _(A) 1 Minute	I _(A) 3 Seconds	Fuses
20BD8P0	5	3	8.1	8	8.8	12	HSJ15
20BD011	7.5	5	11.1	11	12.1	16.5	HSJ20
20BD014	10	7.5	14.7	14	16.5	22	HSJ30
20BD022	15	10	23.3	22	24.2	33	HSJ45
20BD027	20	15	28.9	27	33	44	HSJ60
20BD034	25	20	36.4	34	40.5	54	HSJ70
20BD040	30	25	42.9	40	51	68	HSJ80
20BD052	40	30	55.7	52	60	80	HSJ100
20BD065	50	40	69.7	65	78	104	HSJ150
20BR077	–	50	67.9	65	98	130	HSJ150
20BR077	60	–	84.5	77	85	116	HSJ150
20BR096	–	60	84.5	77	116	154	HSJ150
20BR096	75	–	105.3	96	106	144	HSJ200
20BR125	–	75	105.3	96	144	168	HSJ200
20BR125	100	–	137.1	125	138	163	HSJ250
20BR156	–	100	137.1	125	188	250	HSJ250
20BR156	125	–	171.2	156	172	234	HSJ300
20BR180	–	125	171.2	156	234	312	HSJ300
20BR180	150	–	204.1	180	198	270	HSJ400

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 750 SERIES

Part # 400VAC (x= F or G)	HP Normal Duty	HP Heavy Duty	I (A) Input	Fuses
20x...C2P1	1	1	1.7	HSJ3
20x...C3P5	2	1	2.8	HSJ6
20x...C5P0	3	2	4.5	HSJ6
20x...C8P7	5	3	7.8	HSJ10
20x...C011	7	5	10.7	HSJ15
20x...C015	10	7	14.6	HSJ20
20x...C022	15	10	21.1	HSJ30
20x...C030	20	15	28.7	HSJ40
20x...C037	25	20	35.4	HSJ45
20x...C043	30	25	41.2	HSJ600
20x...C060	40	30	57.4	HSJ80
20x...C072	50	40	70.5	HSJ90
20x...C085	60	50	83.3	HSJ110
20x...C104	75	60	102.9	HSJ150
20x...C140	100	75	137.2	HSJ175
20x...C170	120	100	166.5	HSJ225
20x...C205	150	120	200.8	HSJ300
20x...C260	175	150	254.7	HSJ350
20x...C302	214	175	295.9	HSJ400
20x...C367	270	214	359.5	HSJ500
20x...C456	335	-	446.7	HSJ600

Part # 480VAC (x= F or G)	HP Normal Duty	HP Heavy Duty	I (A) Heavy Duty	Mersen Fuse
20x...D2P1	1	1	1.6	HSJ3
20x...D3P4	2	1	2.6	HSJ6
20x...D5P0	3	2	3.9	HSJ6
20x...D8P0	5	3	6.9	HSJ10
20x...D011	7.5	5	9.5	HSJ15
20x...D014	10	7.5	12.5	HSJ20
20x...D022	15	10	19.9	HSJ30
20x...D027	20	15	24.8	HSJ35
20x...D034	25	20	31.2	HSJ45
20x...D040	30	25	36.7	HSJ50
20x...D052	40	30	47.7	HSJ70
20x...D065	50	40	59.6	HSJ90
20x...D077	60	50	72.3	HSJ100
20x...D096	75	60	90.1	HSJ125
20x...D125	100	75	117.4	HSJ175
20x...D156	125	100	146.5	HSJ200
20x...D186	150	125	174.6	HSJ250
20x...D248	200	150	232.8	HSJ350
20x...D302	250	200	283.5	HSJ400
20x...D361	300	250	338.9	HSJ500
20x...D415	350	-	389.6	HSJ600

MERSEN DRIVE FUSE SELECTION TABLE

ALLEN BRADLEY POWERFLEX 750 SERIES

Part # 600VAC (x= F or G)	HP Normal Duty	HP Heavy Duty	I (A) Input	Fuses
20x...E1P7	0.5	0.5	0.9	HSJ1
20x...E1P7	1	0.5	1.6	HSJ2
20x...E2P7	2	1	2.6	HSJ3
20x...E3P9	3	2	3.7	HSJ5
20x...E6P1	5	3	5.8	HSJ10
20x...E009	7.5	5	8.5	HSJ15
20x...E011	10	7.5	10.4	HSJ15
20x...E017	15	10	16.1	HSJ20
20x...E022	20	15	21	HSJ30
20x...E027	25	20	26	HSJ35
20x...E032	30	25	30	HSJ40
20x...E041	40	30	39	HSJ50
20x...E052	50	40	49	HSJ70
20x...E063	60	50	60	HSJ80
20x...E077	75	60	73	HSJ100
20x...E099	100	75	94	HSJ125
20x...E125	125	100	118	HSJ150
20x...E144	150	125	136	HSJ175
20x...E192	200	150	181	HSJ250
20x...E242	250	200	229	HSJ300
20x...E289	300	-	273	HSJ350

Mersen HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers' recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes for non-bypass mode applications only.